



Model		EH-1004	EH-1008	EH-1011	EH-1014	EH-1017
Spec.	MHz	Splitter	Coupler	Coupler	Coupler	Coupler
Insertion Loss IN --> Out (dB)	5 - 300	3.5	3.0	1.5	0.7	0.5
	300-500	3.8	3.4	1.6	0.9	0.7
	500-750	4.2	3.7	1.8	1.0	0.9
	750-1000	4.5	4	2	1.2	1.0
Tap loss IN --> Tap (dB)	5 - 300	--	8.0	10.9	14.2	17.3
	300-500	--	8.4	11.2	14.7	17.7
	500-750	--	8.9	11.7	15.3	18.1
	750-1000	--	9.2	12.3	15.8	18.5
Isolation Loss Tap --> Tap (dB)	5 - 300	27	25	26	26	26
	300-500	26	26	25	25	25
	500-750	25	25	25	25	25
	750-1000	25	25	25	25	25
Isolation Loss Tap --> Out (dB)	5 - 300	--	26	26	28	30
	300-500	--	26	26	27	29
	500-750	--	25	25	27	29
	750-1000	--	25	25	26	29
Return Loss In (dB)	5 - 300	17	13	17	17	17
	300-500	16	15	16	16	16
	500-750	15	15	15	16	16
	750-1000	15	16	15	15	16
Return Loss Out (dB)	5 - 300	17	16	17	17	17
	300-500	16	15	16	16	16
	500-750	15	15	15	15	15
	750-1000	15	15	15	15	15
Return Loss Tap (dB)	5 - 300	--	16	17	17	17
	300-500	--	16	17	16	16
	500-750	--	15	15	15	15
	750-1000	--	15	15	15	15

Eastern House Electronics Co., Ltd.

No. 177., Zhengdong Rd., Tien Shan Vil., Hemei Township, Changhua country 508, Taiwan, R.O.C.
 Tel: +886-7-569-751~3 Fax: +886-7-568961 Email: info@ehcatv.com.tw http://www.ehcatv.com.tw
 ©2012 Eastern House Electronic Co., Ltd. All rights reserved.